



Package Contents

- 1 PE4104A IP Control Box
- 1 standard rack mount kit
- 1 foot pad set (4 pcs)
- 1 user instructions

Support and Documentation Notice

All information, documentation, firmware, software utilities, and specifications contained in this package are subject to change without prior notification by the manufacturer. To reduce the environmental impact of our products, ATEN documentation and software can be found online at <http://www.aten.com/download/>
Technical Support
www.aten.com/support

Scan for more information

Product Page



User Manual



A Hardware Overview

- 1 LAN port
- 2 reset button (recessed)
- 3 sensor port & LED
- 4 dry-contact port
- 5 power control buttons & LEDs
- 6 device power LED
- 7 grounding terminal
- 8 power outlet sockets
- 9 circuit breaker
- 10 power inlet

B Rack Mount

Desktop Mount

If you wish to keep your unit on a desktop, attach the supplied footpads and place the unit on any appropriate level surface that can safely support its weight plus the weight of its attached cables.

Rack Mount

- 1 Decide where you would rack mount the unit and choose where you would attach the rack mount ear (position 1, 2, 3 or 4). As an example, we will choose to attach the rack mount ear shown above (position 3).
- 2 Align and stabilize the rack mount ear using M3 Philips hex screws.
- 3 Align the unit and rack mount ear to the rack and stabilize using rack screws.
- 4 Let the buttons stabilize in the button holes, and the mounting is complete.

C Installation

- 1 Make sure the unit is properly grounded.
 - Note:** Do not omit this step. Proper grounding helps to prevent damage to the unit from power surges or static electricity.
- 2 For each device you want to connect, connect its power cable to any available outlet on the unit. Optionally, use ATEN Lok-U-Plug cable holders to secure them (see above).
- 3 Connect an internet-enabled LAN cable into the unit's LAN port.
- 4 (Optional) To use a temperature sensor, humidity sensor, or pressure sensor, connect it to the RJ-11 sensor port.
- 5 (Optional) To use a door sensor or a leak detector, connect it to the dry-contact port.
- 6 Plug the power cord to an AC power source.
- 7 Power on the connected devices.